

PUMPROOM

DB PUMPROOM		80A TP		25mmSQ 4C)		FED FROM FP9	
BREAKER	10 SP	10 SP	30ELCB	10 TP	60 TP	20 TP	TOTAL
CONTROL							
CIRCUIT NO	L1	L2	P1	P2	P3	P4	
LOAD/PHASE	LGT	SPARE	SSO	W/PUMP	F/PUMP	JOCKEY	
WIRE(mm)	1C/1.5	SPARE	1C/2.5	4C/2.5	4C/10	4C/4.0	
Watts	288	SPARE	2000	2200	30000	7500	41,988
KW	0.288	SPARE	2	2.2	30	7.5	42
Div KW	0.3	SPARE	1.6	1.8	30.0	7.5	41
					DIV LOAD		41

			SINGLE PHASE (RED,YELLOW,BLUE)
			THREE PHASE

100 MEN ACCOMMODATION HANGAR

DB-1 & DB-2					45A TP		6mmSQ 4C)			FED FROM FP4								
BREAKER CONTROL	10SP	10SP	10SP	10SP	10SP	10SP		30ELCB	30ELCB	30ELCB	20A SP	20A SP	5A SP	5A SP	5A SP	5A SP	5A SP	TOTAL
CIRCUIT NO	L1	L2	L3	L4	L5	L6	L7	P1	P2	P3	P4	P5	P6	P7	P8	P9	P10	
LOAD/PHASE	LGT	LGT	LGT	LGT	LGT	LGT	SPARE	SSO	SSO	SSO	SSO	SSO	EXTRACT	EXTRACT	CALORIFIER	CALORIFIER	SPARE	
WIRE(mm)	1C/1.5	1C/1.5	1C/1.5	1C/1.5	1C/1.5	1C/1.5	SPARE	1C/2.5	1C/2.5	1C/2.5	1C/2.5	1C/2.5	1C/1.5	1C/1.5	4C/4.0	4C/4.0	SPARE	
Watts	1260	660	660	660	660	660	SPARE	2000	2000	2000	2000	2000	157	157	6500	6500	SPARE	27,874
KW	1.26	0.66	0.66	0.66	0.66	0.66	SPARE	2	2	2	2	2	0.157	0.157	6.5	6.5	SPARE	28
Div KW	1.3	0.7	0.7	0.7	0.7	0.7	SPARE	1.6	1.6	1.6	1.6	1.6	0.1	0.1	6.5	6.5	SPARE	26

			SINGLE PHASE (RED,YELLOW,BLUE)
			THREE PHASE

FUEL PUMP

	DB FP				20A TP MAIN BREAKER			4mmSQ 4C)			FED FROM FP3			
BREAKER	10 SP	10 SP		30ELCB	30ELCB	30ELCB	20A SP	20A SP	5A SP	5A SP	5A SP	20A TP	TOTAL	
CONTROL														
CIRCUIT N	L1	L2	L4	P1	P2		P4	P5	P6	P7	P14	P15		
LOAD/PHA	LGT	LGT	SPARE	SSO	SSO		HD1	HD2	EXTRACT	EXTRACT	FCU	ODU2		
WIRE(mm	1C/1.5	1C/1.5	SPARE	1C/2.5	1C/2.5		1C/2.5	1C/2.5	1C/1.5	1C/1.5	1C/1.6	1C/2.5		
Watts	900	900	SPARE	3679	3680		1000	1000	157	550	1000	5700	9,407	
KW	0.9	0.9	SPARE	3.679	3.68		1	1	0.157	0.55	1	5.7	9	
Div KW	0.9	0.9	SPARE	2.9	2.9		0.8	0.8	0.1	0.4	0.8	5.7	9	

			SINGLE PHASE (RED,YELLOW,BLUE)	EF	Extract Fan
			THREE PHASE	FCU	Fan Control Unit/Casette

SUBSTATION

DB SUBSTATION			30A SP MAIN BREAKER			6mmSQ (3C)	FED FROM LOCAL	
BREAKER	10 SP	10 SP		30ELCB	30ELCB	30ELCB	TOTAL	
CONTROL								
CIRCUIT N°	L1	L2	L4	P1	P2	L4		
LOAD/PHASE	LGT	LGT	SPARE	SSO	SSO	SPARE		
WIRE(mm²)	1C/1.5	1C/1.5	SPARE	1C/2.5	1C/2.5	SPARE		
Watts	900	900	SPARE	3679	3680	SPARE	5,700	
KW	0.9	0.9	SPARE	3.679	3.68	SPARE	6	
Div KW	0.9	0.9	SPARE	2.9	2.9	SPARE	6	

SINGLE PHASE (RED,YELLOW,BLUE)

THREE PHASE

GATE-HOUSE 2

DB GH-2			30A SP MAIN BREAKER			6mmSQ (3C)	
BREAKER	10 SP	10 SP		30ELCB	30ELCB	30ELCB	TOTAL
CONTROL							
CIRCUIT N	L1	L2	L4	P1	P2	L4	
LOAD/PH	LGT	LGT	SPARE	SSO	SSO	SPARE	
WIRE(mm	1C/1.5	1C/1.5	SPARE	1C/2.5	1C/2.5	SPARE	
Watts	900	900	SPARE	3679	3680	SPARE	5,700
KW	0.9	0.9	SPARE	3.679	3.68	SPARE	6
Div KW	0.9	0.9	SPARE	2.9	2.9	SPARE	6

[illegible]

NOTES:

1. ALL CABLES ENTIRELY TO EQUIPMENT LOCATED OUTDOORS AND IN WASH DOWN AREAS SHALL BE FROM BELOW.
2. SUFFICIENT CABLE SPARE LENGTHS SHALL BE PROVIDED FOR EQUIPMENT WHICH NEEDS FUTURE ADJUSTMENTS.
3. SINGLE CORE CABLES FOR PHASES AC SHALL BE RUN IN TRUFFLE FORMATION.
4. THE MINIMUM BENDING RADIUS OF CABLES SPECIFIED BY THE MANUFACTURER SHALL BE ADHERED TO.
5. ON CROSSING PIPES/SURFACES, A MINIMUM DISTANCE OF 150mm SEPARATION SHALL BE MAINTAINED AND CONCRETE SLABS SHALL BE USED TO SEPARATE THE VERTICAL SEPARATION FROM COMMUNICATION CABLES SHALL BE 200mm MINIMUM.
6. ALL THE DIMENSIONS SHOWN ON DRAWINGS ARE METRIC (in mm)
7. THE INLET OF THESE DRAWINGS IS TO GUIDE THE CONTRACTOR IN THE SCHEME OF WORKS. CONTRACTOR SHALL MAKE PROPER SHOP DRAWINGS FOR THE APPROVAL OF THE ENGINEER AND SUMIT IT BEFORE THE WORK COMMENCES AT SITE.
8. ALL ELECTRIC WORK SHALL BE EXECUTED IN STRICT ACCORDANCE WITH THE PROJECT SPECIFICATION.
9. THE ROUTING OF CABLES SHOWN ON DRAWINGS IS FOR GUIDANCE ONLY IT SHALL BE THE RESPONSIBILITY OF THE CONTRACTOR TO CHECK AS THE STAGE OF TENURE. THE RUNS OF ALL CABLES IN RELATION TO STRUCTURAL RESTRICTION SO THAT ALL MATERIALS SUCH AS CONCRETE, STEEL ACCESSORIES ARE INCLUDED IN ITS PLANNING. ACTUAL LOCATIONS OF ALL OUTLETS MUST BE VERIFIED BY THE SITE ENGINEER BEFORE INSTALLATION COMMENCES.
10. ALL ELECTRICAL EQUIPMENT SHALL BE SUPPLIED BY AN APPROVED MANUFACTURER AND THE CONTRACTOR SHALL ENSURE THAT ALL EQUIPMENT ARE SATISFIED FOR THE PURPOSE FOR WHICH IT IS INTENDED AND THAT IT IS FUNCTIONING PROPERLY AFTER INSTALLATION.

LIGHTING AND SMALL POWER NOTES:-

1. MOUNTING HEIGHTS SHALL BE GENERALLY AS INDICATED BELOW OR AS INSTRUCTED BY THE ENGINEER WITHOUT ANY COST TO THE CONTRACTOR TO THE FOLLOWING:
 - LIGHTING SWITCH = 1500mm AFFL.
 - GENERAL SOCKET OUTLET = 450mm AFFL.
 - SOCKET OUTLET AT COUNTER = 1100mm AFFL.
 - HAND DRYERS = AS MENTIONED IN INTERIOR DESIGN DRAWINGS
- ISOLATOR SWITCH = ADJACENT TO EQUIPMENT
2. WIRE SIZES SHALL BE STRICTLY FOLLOWED ACCORDING TO THE INDICATED SIZES SHOWN IN THE PANEL DETAILS. WIRES SHALL BE COLOR CODED AS SPECIFIED.
3. WIRING FOR SMALL POWER AND LOW CURRENT CIRCUITS SHALL BE TOTALLY SEGREGATED THIS IS INCLUDING PANELS, RACEWAYS AND WIRES, SWITCHES ETC.
4. ALL EQUIPMENTS DESIGNATED FOR ELECTRIC APPLIANCES OR EQUIPMENT SHALL BE LABELED WITH THE EQUIPMENT REFERENCE.
5. CONDUIT INSTALLATIONS SHALL BE AS PER SPECS.
6. REFER TO ARCHITECTURAL REFLECTED CEILING DRAWINGS AND FINISHING TABLES FOR EXACT ARRANGEMENT OF LUMINAIRE.
7. CORD (FLEXIBLE) OUTLET SHALL BE INSTALLED FOR ANY REMOTE CONTROL.
8. WIRING FOR LIGHTING CIRCUITS ARE FOR GUIDANCE ONLY THE CONTRACTOR MAY CHOOSE THE MOST CONVENIENT ROUTE TO AVOID THE PROJECT SPECIFICATIONS AND SHOW IT IN HIS SHOP DRAWINGS.
9. THE CONTRACTOR SHALL SUBMIT PANEL BOARDS DETAILS ALONG WITH THE REQUIRED SUBMITTALS AND SHOP DRAWINGS SHOWING:
 - CIRCUIT REFERENCE SHOWN ON LAYOUTS
 - ACTUAL LOAD OF EACH CIRCUIT PER PHASE IN VA
 - SUMMATION OF EACH PHASE LOAD ASSUMING 3 PHASE LOAD
 - AREAS SERVED BY EACH CIRCUIT
 - RATING OF ALL COMPONENTS
 - WIRE SIZE AND No. OF WIRES
 - SCHEMATIC DIAGRAMS FOR CONTROL CIRCUITS IF ANY ENCLOSURE AND BUREAU SPECIFICATIONS
10. CONVENIENCE SOCKET OUTLETS FRO FREQUENCY PANEL C UPS SHALL BE SELECTED WITH DIFFERENT COLOR COVER PLATE

TENDER

STAGE		TENDER	
	INITIAL	SIGN	DATE
G4 Project Engineer			
Project Manager			
Project Architect			
Client			

REV	DESCRIPTION	DATE	INITIAL

CLIENT

 SOUTHERN AFRICAN
DEVELOPMENT COMMUNITY

PROJECT	SADC STANDBY FORCE REGIONAL LOGISTICS DEPOT, AT RASESA, GABORONE, BOTSWANA,
DRAWING TITLE	

DB ONE-LINE
DRAWING-ARMOURY, KITCHEN,
WAREHOUSE, GYM, PUMPROOM



G4 CONSULTING ENGINEERS
PRIVATE BAG BR 297
GABORONE
BOTSWANA

TEL. 3972510 FAX 3972504

DESIGNED : HG	JOB NO. : 94448
DRAWN : HG	SCALE : 1:100
APPROVED :	DATE : JUN 2021

DRAWING NO.	REV.
SADC/ELEC/4024C	1